

Für die Übertragung steht Ihnen folgender Frequenzbereich zur Verfügung:

Frequenzbereich	Bandbreite	Anzahl Frequenzen
626 - 668 MHz	42 MHz	max. 1680

Die Sender und Empfänger verfügen über jeweils 20 Kanalbänke, auf denen werksseitig Frequenz-Presets voreingestellt sind. Innerhalb einer Kanalbank sind die Frequenz-Presets untereinander intermodulationsfrei. Sie sind nicht veränderbar.

In der Kanalbank **U** können Sie in 25-kHz-Schritten Frequenzen frei einstellen und abspeichern. Diese sind unter Umständen nicht intermodulationsfrei.

Die Frequenz-Presets in den Kanalbänken **1** bis **20** sind in der Tabelle auf den Innenseiten dargestellt.

#### Rahmenbedingungen und Einschränkungen für die Nutzung von Frequenzen

In Ihrem Land gelten möglicherweise gesonderte Rahmenbedingungen und Einschränkungen für die Nutzung von Frequenzen.

Informieren Sie sich vor der Inbetriebnahme des Produktes unter folgender Adresse:

[www.sennheiser.com/frequency-information](http://www.sennheiser.com/frequency-information)

Transmitters and receivers are available in the following frequency range:

Frequency range	Bandwidth	Number of frequencies
626 - 668 MHz	42 MHz	max. 1680

Transmitters and receivers have 20 frequency banks respectively. Each of the channels in the frequency banks has been factory-preset to a frequency. These frequency presets within one frequency bank are intermodulation-free. They cannot be changed.

The frequency bank **U** allows the user to store individual frequencies which are freely selectable in 25-kHz steps. It might be that these frequencies are not intermodulation free.

The table printed inside lists the frequency presets in the frequency banks **1** to **20**.

#### Conditions and restrictions for using frequencies

There may be special conditions and restrictions for using frequencies in your country.

Before putting the product into operation, find the information for your country at the following address:

[www.sennheiser.com/frequency-information](http://www.sennheiser.com/frequency-information)



## 626 - 668 MHz

### Frequenzbereich B / Frequency range B

#### Zusatzinformationen für Systeme der Serie evolution wireless 100 G4

#### Additional information for Sennheiser evolution wireless 100 G4 systems

## Frequenzbereich B / Frequency range B: 626 - 668 MHz

### EBU TV Channels

CH 40: 622 - 630 MHz	CH 41: 630 - 638 MHz	CH 42: 638 - 646 MHz
CH 43: 646 - 654 MHz	CH 44: 654 - 662 MHz	CH 45: 662 - 670 MHz

Channel	Bank 1	Bank 2	Bank 3	Bank 4	Bank 5	Bank 6	Bank 7	Bank 8	Bank 9	Bank 10
1	626.200	630.200	638.200	646.200	654.200	662.200	630.200	638.200	646.200	662.600
2	626.600	630.600	638.600	646.600	654.600	662.600	630.600	638.600	646.600	664.200
3	627.200	631.200	639.200	647.200	655.200	664.200	631.200	639.200	647.200	665.400
4	628.400	632.000	640.000	648.000	656.000	665.400	632.000	640.000	648.000	666.400
5	629.800	633.200	641.200	649.200	657.200	666.400	633.200	641.200	649.200	667.200
6	631.400	635.600	643.600	651.600	659.600	667.200	634.800	642.800	650.800	667.800
7	632.200	637.800	645.800	653.800	661.800	667.800	638.600	646.600	654.600	626.200
8	634.200	636.900	644.900	652.900	660.900	663.275	639.900	647.900	655.900	626.600
9	637.600	632.475	640.475	648.475	656.475	664.625	642.600	650.600	658.600	627.550
10	632.650	634.125	642.125	650.125	658.125		643.100	651.100	659.100	628.250
11	633.550	634.575	642.575	650.575	658.575		644.800	652.800	660.800	628.700
12	635.300	636.475	644.475	652.475	660.475		645.500	653.500	661.500	629.550

Channel	Bank 11	Bank 12	Bank 13	Bank 14	Bank 15	Bank 16	Bank 17	Bank 18	Bank 19	Bank 20
1	626.200	630.200	626.200	630.200	626.200	630.200	638.200	646.200	654.200	662.200
2	626.600	631.400	626.600	630.600	626.600	632.400	640.400	648.400	656.400	662.600
3	627.200	633.000	627.200	631.200	627.200	634.800	642.800	650.800	658.800	663.150
4	628.000	635.000	628.400	632.000	628.000	636.000	644.000	652.000	660.000	663.850
5	638.200	637.200	629.200	633.200	628.500	636.800	644.800	652.800	660.800	664.275
6	639.400	646.600	654.200	634.800	629.200	637.400	645.400	653.400	661.400	664.850
7	641.000	649.200	655.600	637.000	662.200	637.800	645.800	653.800	661.800	665.650
8	643.000	652.200	658.000	662.200	663.100	631.100	639.100	647.100	655.100	666.125
9	645.200	662.200	659.600	664.600	664.600	631.525	639.525	647.525	655.525	666.750
10	655.600	662.600	654.700	667.800	666.300	633.425	641.425	649.425	657.425	667.650
11	658.600	663.200	657.250	662.700	667.400	633.875	641.875	649.875	657.875	
12	661.200	664.000	660.050	666.100	663.750	635.525	643.525	651.525	659.525	