



SENNHEISER

780 - 822 MHz

Frequenzbereich D / Frequency range D

Zusatzinformationen für Systeme der Serie
evolution wireless IEM G4

Additional information for Sennheiser
evolution wireless IEM G4 systems

DE

Für die Übertragung steht Ihnen folgender Frequenzbereich zur Verfügung:

Frequenzbereich	Bandbreite	Anzahl Frequenzen
780 - 822 MHz	42 MHz	max. 1680

Die Sender und Empfänger verfügen über jeweils 20 Kanalbänke, auf denen werksseitig Frequenz-Presets voreingestellt sind. Innerhalb einer Kanalbank sind die Frequenz-Presets untereinander intermodulationsfrei. Sie sind nicht veränderbar.

In den Kanalbänken **U1 bis U6** können Sie in 25-kHz-Schritten Frequenzen frei einstellen und abspeichern. Diese sind unter Umständen nicht intermodulationsfrei.

Die Frequenz-Presets in den Kanalbänken **1 bis 20** sind in der Tabelle auf der folgenden Seite dargestellt.

Rahmenbedingungen und Einschränkungen für die Nutzung von Frequenzen

In Ihrem Land gelten möglicherweise gesonderte Rahmenbedingungen und Einschränkungen für die Nutzung von Frequenzen.

Informieren Sie sich vor der Inbetriebnahme des Produktes unter folgender Adresse:

www.sennheiser.com/frequency-information

EN

Transmitters and receivers are available in the following frequency range:

Frequency range	Bandwidth	Number of frequencies
780 - 822 MHz	42 MHz	max. 1680

Transmitters and receivers have 20 frequency banks respectively. Each of the channels in the frequency banks has been factory-preset to a frequency. These frequency presets within one frequency bank are intermodulation-free. They cannot be changed.

The frequency banks **U1 to U6** allow the user to store individual frequencies which are freely selectable in 25-kHz steps. It might be that these frequencies are not intermodulation free.

The table printed on the following page lists the frequency presets in the frequency banks **1 to 20**.

Conditions and restrictions for using frequencies

There may be special conditions and restrictions for using frequencies in your country.

Before putting the product into operation, find the information for your country at the following address:

www.sennheiser.com/frequency-information

Sennheiser electronic GmbH & Co. KG

Am Labor 1, 30900 Wedemark, Germany, www.sennheiser.com
Publ. 01/18, 578640/A01

Frequenzbereich D / Frequency range D: 780 - 822 MHz

Channel	Bank 1	Bank 2	Bank 3	Bank 4	Bank 5	Bank 6	Bank 7	Bank 8	Bank 9	Bank 10
1	780.000	780.000	790.200	798.200	806.200	814.200	782.200	790.200	798.200	806.200
2	780.400	780.600	790.600	798.600	806.600	814.600	782.600	790.600	798.600	806.600
3	782.000	782.200	791.200	799.200	807.200	815.200	783.200	791.200	799.200	807.200
4	783.000	783.000	792.000	800.000	808.000	816.000	784.000	792.000	800.000	808.000
5	784.400	784.200	793.200	801.200	809.200	817.200	785.200	793.200	801.200	809.200
6	785.200	786.800	795.600	803.600	811.600	819.600	786.800	794.800	802.800	810.800
7	788.000	788.600	797.800	805.800	813.800	821.800	790.600	798.600	806.600	814.600
8	788.600	789.600	796.900	804.900	812.900	820.900	791.900	799.900	807.900	815.900
9	789.800	790.000	798.500	780.000	819.000	780.000	794.600	802.600	810.600	818.600
10	781.300	784.700	801.200	780.500	821.800	781.600	795.100	803.100	811.100	819.100
11	795.000	798.400	807.200	781.600	780.000	788.600	796.800	804.800	812.800	820.800
12	803.800	801.800	808.300	807.700	780.500	791.400	797.500	805.500	813.500	821.500
13	805.800	809.000	812.400	809.200	781.600	794.600	810.600	818.600	780.500	780.200
14	815.000	816.600	814.700	810.900	784.700	803.400	803.600	811.600	781.400	783.600
15	820.800	821.700	818.500	813.200	786.400	806.800	813.100	815.300	789.100	790.400
16	821.200	815.700	820.200	821.000	788.700	783.500	818.100	821.100	791.000	801.900

Channel	Bank 11	Bank 12	Bank 13	Bank 14	Bank 15	Bank 16	Bank 17	Bank 18	Bank 19	Bank 20
1	780.200	782.200	780.200	782.200	780.200	782.200	790.200	798.200	806.200	819.100
2	780.600	783.400	780.600	782.600	780.600	784.400	792.400	800.400	808.400	819.600
3	781.200	785.000	781.200	783.200	781.200	786.800	794.800	802.800	810.800	820.250
4	782.000	787.000	782.000	784.000	782.000	788.000	796.000	804.000	812.000	820.700
5	792.200	789.200	806.200	785.200	814.200	788.800	796.800	804.800	812.800	821.550
6	793.400	798.600	806.700	786.800	814.700	789.400	797.400	805.400	813.400	821.950
7	795.000	801.200	807.400	789.000	815.400	789.800	797.800	805.800	813.800	
8	797.000	804.200	809.000	814.200	817.000	783.100	791.100	799.100	807.100	
9	799.200	814.200	810.100	816.600	818.100	796.800	804.800	780.200	781.800	
10	809.600	814.600	811.600	819.800	819.600	798.400	806.400	780.700	784.100	
11	812.600	815.200	812.500	814.700	820.500	806.200	814.600	781.800	785.800	
12	815.200	816.000	813.800	818.100	821.800	809.000	817.400	784.100	788.600	
13	798.300	783.900	817.800		785.800	817.200	820.650	785.800	790.100	
14	802.700	788.500	819.500		787.900	820.400	809.500	788.600	794.800	
15	807.300	805.500	821.600		789.800	796.300	811.200	810.100	820.900	
16	810.700						784.600	813.900	821.600	