



SENNHEISER

606 - 648 MHz

Frequenzbereich GB / Frequency range GB

**Zusatzinformationen für Systeme der Serie
evolution wireless IEM G4**

**Additional information for Sennheiser
evolution wireless IEM G4 systems**

DE

Für die Übertragung steht Ihnen folgender Frequenzbereich zur Verfügung:

Frequenzbereich	Bandbreite	Anzahl Frequenzen
606 - 648 MHz	42 MHz	max. 1680

Die Sender und Empfänger verfügen über jeweils 20 Kanalbänke, auf denen werksseitig Frequenz-Presets voreingestellt sind. Innerhalb einer Kanalbank sind die Frequenz-Presets untereinander intermodulationsfrei. Sie sind nicht veränderbar.

In den Kanalbänken **U1 bis U6** können Sie in 25-kHz-Schritten Frequenzen frei einstellen und abspeichern. Diese sind unter Umständen nicht intermodulationsfrei.

Die Frequenz-Presets in den Kanalbänken **1 bis 20** sind in der Tabelle auf der folgenden Seite dargestellt.

Rahmenbedingungen und Einschränkungen für die Nutzung von Frequenzen

In Ihrem Land gelten möglicherweise gesonderte Rahmenbedingungen und Einschränkungen für die Nutzung von Frequenzen.

Informieren Sie sich vor der Inbetriebnahme des Produktes unter folgender Adresse:

www.sennheiser.com/frequency-information

EN

Transmitters and receivers are available in the following frequency range:

Frequency range	Bandwidth	Number of frequencies
606 - 648 MHz	42 MHz	max. 1680

Transmitters and receivers have 20 frequency banks respectively. Each of the channels in the frequency banks has been factory-preset to a frequency. These frequency presets within one frequency bank are intermodulation-free. They cannot be changed.

The frequency banks **U1 to U6** allow the user to store individual frequencies which are freely selectable in 25-kHz steps. It might be that these frequencies are not intermodulation free.

The table printed on the following page lists the frequency presets in the frequency banks **1 to 20**.

Conditions and restrictions for using frequencies

There may be special conditions and restrictions for using frequencies in your country.

Before putting the product into operation, find the information for your country at the following address:

www.sennheiser.com/frequency-information

Sennheiser electronic GmbH & Co. KG

Am Labor 1, 30900 Wedemark, Germany, www.sennheiser.com
Publ. 01/18, 578642/A01

Frequenzbereich GB / Frequency range GB: 606 - 648 MHz

Channel	Bank 1	Bank 2	Bank 3	Bank 4	Bank 5	Bank 6	Bank 7	Bank 8	Bank 9	Bank 10
1	606.500	614.500	622.500	630.500	638.500	606.900	606.500	614.900	606.500	611.600
2	607.500	615.500	623.500	631.500	639.500	607.500	607.500	615.500	607.100	612.000
3	608.300	616.300	624.300	632.300	640.300	608.800	608.800	616.800	607.900	612.600
4	610.400	618.400	626.400	634.400	642.400	610.400	609.500	618.400	608.400	619.600
5	612.800	620.800	628.800	636.800	644.800	612.800	612.800	620.800	610.000	620.100
6	606.900	614.900	622.900	630.900	638.900	617.800	622.500	625.800	612.400	620.800
7	613.500	621.500	629.500	637.500	645.500	621.000	626.800	629.000	615.200	627.900
8	608.800	616.800	624.800	632.800	640.800	606.500	629.000	614.500	618.900	
9	611.300	619.300	627.300	635.300	643.300	608.300	606.900	616.300	624.500	
10						609.500	608.300	617.500	628.100	
11						615.000	625.300	623.000	632.400	
12						619.300	610.400	627.300	637.100	
13							623.600		644.600	
14									647.300	
15									606.100	
16									622.300	

Channel	Bank 11	Bank 12	Bank 13	Bank 14	Bank 15	Bank 16	Bank 17	Bank 18	Bank 19	Bank 20
1	611.600	611.600	619.600	630.900	622.500	622.500	622.900	614.500	614.500	606.500
2	612.000	612.000	620.000	631.500	624.300	623.500	623.500	616.300	614.900	607.100
3	612.600	612.600	620.600	632.800	625.500	624.800	624.800	617.500	616.800	608.000
4	619.600	627.600	627.600	634.400	626.400	625.500	626.400	618.400	617.500	609.200
5	620.100	628.100	628.100	636.800	628.800	628.800	628.800	620.800	630.500	611.000
6	620.800	628.800	628.800	641.800	631.500	638.500	633.800	623.500	634.300	613.400
7				645.000	633.000	642.800	637.000	625.000	636.000	623.400
8				630.500	641.400	622.900	622.500	633.400	640.700	630.800
9				632.300	645.000	641.300	624.300	637.000	645.000	638.500
10				633.500	622.900	645.000	625.500	614.900	618.400	646.500
11				639.000	623.500	624.300	631.000	615.500	620.800	618.200
12				643.300	624.800	626.400	635.300	616.800	631.600	646.900
13					635.800	639.600		627.800	638.500	609.700
14					639.200			631.200	642.200	616.800
15					643.900			635.900	615.500	633.000
16									616.300	647.600