



SENNHEISER

566 - 608 MHz

## Frequenzbereich G / Frequency range G

Zusatzinformationen für Systeme der Serie  
evolution wireless IEM G4

Additional information for Sennheiser  
evolution wireless IEM G4 systems

DE

Für die Übertragung steht Ihnen folgender Frequenzbereich zur Verfügung:

Frequenzbereich	Bandbreite	Anzahl Frequenzen
566 - 608 MHz	42 MHz	max. 1680

Die Sender und Empfänger verfügen über jeweils 20 Kanalbänke, auf denen werksseitig Frequenz-Presets voreingestellt sind. Innerhalb einer Kanalbank sind die Frequenz-Pre-sets untereinander intermodulationsfrei. Sie sind nicht veränderbar.

In den Kanalbänken **U1 bis U6** können Sie in 25-kHz-Schritten Frequenzen frei einstellen und abspeichern. Diese sind unter Umständen nicht intermodulationsfrei.

Die Frequenz-Pre-sets in den Kanalbänken **1 bis 20** sind in der Tabelle auf der folgenden Seite dargestellt.

### Rahmenbedingungen und Einschränkungen für die Nutzung von Frequenzen

In Ihrem Land gelten möglicherweise gesonderte Rahmenbedingungen und Einschränkungen für die Nutzung von Frequenzen.

Informieren Sie sich vor der Inbetriebnahme des Produktes unter folgender Adresse:

[www.sennheiser.com/frequency-information](http://www.sennheiser.com/frequency-information)

EN

Transmitters and receivers are available in the following frequency range:

Frequency range	Bandwidth	Number of frequencies
566 - 608 MHz	42 MHz	max. 1680

Transmitters and receivers have 20 frequency banks respectively. Each of the channels in the frequency banks has been factory-preset to a frequency. These frequency presets within one frequency bank are intermodulation-free. They cannot be changed.

The frequency banks **U1 to U6** allow the user to store individual frequencies which are freely selectable in 25-kHz steps. It might be that these frequencies are not intermodulation free.

The table printed on the following page lists the frequency presets in the frequency banks **1 to 20**.

### Conditions and restrictions for using frequencies

There may be special conditions and restrictions for using frequencies in your country.

Before putting the product into operation, find the information for your country at the following address:

[www.sennheiser.com/frequency-information](http://www.sennheiser.com/frequency-information)

Sennheiser electronic GmbH & Co. KG

Am Labor 1, 30900 Wedemark, Germany, [www.sennheiser.com](http://www.sennheiser.com)  
Publ. 01/18, 578643/A01

## Frequenzbereich G / Frequency range G: 566 - 608 MHz

Channel	Bank 1	Bank 2	Bank 3	Bank 4	Bank 5	Bank 6	Bank 7	Bank 8	Bank 9	Bank 10
1	566.200	572.200	578.200	584.200	590.200	596.200	602.200	566.500	572.500	578.500
2	566.600	572.600	578.600	584.600	590.600	596.600	602.600	567.500	573.500	579.500
3	568.200	574.200	580.200	586.200	592.200	598.200	604.200	568.100	574.100	580.100
4	569.400	575.400	581.400	587.400	593.400	599.400	605.400	569.500	575.500	581.500
5	570.400	576.400	582.400	588.400	594.400	600.400	606.400	569.900	575.900	581.900
6	571.200	577.200	583.200	589.200	595.200	601.200	607.200	570.700	576.700	582.700
7	571.800	577.800	583.800	589.800	595.800	601.800	607.800	584.200	590.200	596.200
8	567.275	573.275	579.275	585.275	591.275	597.275	603.275	584.950	590.950	596.950
9	573.700	579.700	585.700	591.700	597.700	603.700	566.200	585.500	591.500	597.500
10	575.950	581.950	587.950	593.950	599.950	605.950	566.650	586.450	592.450	598.450
11	577.250	583.250	589.250	595.250	601.250	607.250	567.950	587.700	593.700	599.700
12	577.800	583.800	589.800	595.800	601.800	607.800	568.500	588.200	594.200	600.200
13	581.650	587.650	593.650	599.650	605.650	572.200	570.200	602.600	602.200	566.500
14	583.100	589.100	595.100	601.100	607.100	572.650	571.350	603.750	602.900	567.150
15	586.800	592.800	598.800	604.800	566.200	575.550	572.900	607.100	603.350	568.200
16	589.250	595.250	601.250	607.250	566.650	577.100	576.200	607.550	604.250	569.650

Channel	Bank 11	Bank 12	Bank 13	Bank 14	Bank 15	Bank 16	Bank 17	Bank 18	Bank 19	Bank 20
1	566.200	574.200	582.200	590.200	598.200	606.200	566.200	574.200	566.200	574.200
2	566.600	574.600	582.600	590.600	598.600	606.600	566.600	575.400	566.600	574.600
3	567.200	575.200	583.200	591.200	599.200	607.200	567.200	577.000	567.200	575.200
4	568.000	576.000	584.000	592.000	600.000	608.000	568.000	579.000	568.000	576.000
5	569.200	577.200	585.200	593.200	601.200	598.200	582.200	581.200	569.600	577.600
6	571.600	579.600	587.600	595.600	603.600	599.400	583.400	590.600	571.800	579.800
7	573.800	581.800	589.800	597.800	605.800	601.000	586.200	593.200	590.200	598.200
8	572.900	580.900	588.900	596.900	604.900	603.200	587.800	596.200	591.400	599.400
9	574.500	582.500	591.700	566.200	574.200	598.950	598.600	606.200	593.100	601.100
10	577.200	585.200	594.000	566.700	574.700	600.050	601.000	606.600	595.000	603.000
11	582.000	590.000	597.200	567.800	575.800	601.500	603.600	607.200	597.100	605.100
12	583.100	591.100	597.900	570.100	578.100	604.250	605.600	608.000	597.600	605.600
13	585.900	593.900	601.000	571.800	579.800	582.200	606.500	569.750	606.200	566.300
14	591.900	599.900	605.000	574.600	582.600	582.750	607.050	570.700	606.650	566.950
15	594.000	602.000	606.600	575.300	583.300	583.450	607.750	572.050	607.300	568.800
16	595.700	603.700	607.100	577.800	585.800	586.350		573.550		569.250